

BackLED S Plus G3

LED moduly pro světelnou reklamu a osvětlení pozadí



Vlastnosti produktu

- Připojeno ohebnými kabely
- Stupeň krytí (moduly): IP66
- Index podání barev R_a : > 80
- Životnost (L70/B50): 50.000 h

Výhody produktu

- Rovnoměrné osvětlení s velkou roztečí LED díky technologii Square Lens
- Moduly jsou kompatibilní s montážním profilem BackLED
- Podstatně vyšší provozní účinnost ve srovnání se systémy bez čoček
- Několik možností pro rychlou a jednoduchou montáž: šrouby nebo nasazením
- Konzistentní bílé světlo (standardní odchylka indexu podání barev SDCM: < 3)
- Záruka 5 let

Druh použití

- Světelné nápisy a světelná reklama
- Podsvícení velkých a/nebo plochých kazetových písmen
- Trvalé venkovní použití v uzavřených světelných boxech nebo kazetových písmenech

Technický list řady výrobků

Výbava / příslušenství

- Montážní profil BackLED BA-SM-MP
 - K dodání několik typů napájecích jednotek OPTOTRONIC 12 V
-

Pokyny k použití

Podrobnější informace k použití a grafiku najdete v technickém listu.

Text pro technický lis

- Installation of LED modules (with power supplies) needs to be made under consideration of all valid regulations and norms.
 - Installation by qualified electrician only.
 - Please see the relevant application guides and instructions sheets for more detailed safety and mounting information. Additional information is available on request.
 - Complies with IEC/EN 61547
 - Complies with IEC/EN 61000-3-2
 - Complies with EN 55015, CISPR 15
 - Complies with IEC/EN 61347-1
 - Complies with IEC/EN 61347-2-13
 - Parallel connection is mandatory for safe electrical operation. Serial connection of LED modules is strongly discouraged. Unbalanced voltage drop in serial connection can cause hazardous overload and damage the LED module.
 - Electrical contact is achieved with the contact cables or the terminals of the module. Please refer to the technical data for maximum number of LED modules that can be operated on one control gear.
 - In order to operate OSRAM LED modules safely, it is absolutely necessary to operate them with an electronically stabilized power supply that protects against short circuits, overload and overheating.
 - In case other power supplies than OSRAM OPTOTRONIC are used, compliance to the necessary operating parameters (voltage, current, power) has to be ensured.
 - Pay attention to polarity! Wrong polarity can cause destruction or malfunction of the module.
 - Conducting paths on the circuit board must not be damaged or destroyed during installation.
 - The LED module itself and all its components must not be stressed mechanically.
 - Operation in or under water is prohibited.
 - To avoid mechanical damage, the LED modules have to be attached securely to the intended mounting surface. It is recommended to avoid heavy vibration.
 - In case that the LED module is equipped with a pre-mounted double-sided adhesive tape, OSRAM assumes no liability and provides no guarantee for a permanent adherence of the modules to the surface. OSRAM recommends fixation of the modules by means of suitable screws.
 - Complies with IEC 61347-1 cl. 18.3, cl. 18.4, IEC 60695-2-10, IEC 60695-11-5, IEC 60695-11-10 (classification V-0)
 - All the technical parameters apply to the entire module. In view of the complex manufacturing process for light emitting diodes, the specified typical values for the technical LED parameters are merely statistical values that do not necessarily correspond to the actual technical parameters of an individual product; individual products may vary from the typical values.
 - Module contains no PVC material.
 - To ensure uniform illumination, a reflective matt white surface is generally recommended for all internal frame walls and back panels of light boxes.
 - LED modules are dimmable by means of PWM (pulse width modulation). It is recommended using the following OSRAM control gears: OPTOTRONIC OT DIM or OPTOTRONIC 24 V power supplies with integrated 1...10 V dimming interface.
 - The module may cause noises during dimming. If a dimming operation is required, it is recommended to check the dimming operation for noises before final installation.
-

Technická podpora a podpora prodeje

Technický list řady výrobků

Technická podpora a podpora prodeje www.osram.cz

Ecodesign regulation information:

- This product is considered to be a "containing product" in the sense of Regulations (EU) 2019/2020 and (EU) 2019/2015.
- Tolerances of the reported values, are according to LED Modules Performance standard IEC/EN 62717.
- In general, the replacement of the contained light sources without permanent damage to the product with the use of common available tools is possible in the final application when they can be dismantled from the installation environment and substituted for the necessary number of light sources restoring its full electrical/mechanical/thermal/optical functionality by means of a professional installer.
- Dismantling of light sources from containing products at end of life: Containing products with light sources which are scalable in length can be cut to the length of the contained light source and if applicable mechanically detached from protective and/or optical covers. Containing products shall be separated from building material and/or from other additional mounting accessories by means of a professional installer. Separate control gear and light sources must be disposed of at certified disposal companies in accordance with Directive 2012/19/EU (WEEE) in the EU and with Waste Electrical and Electronic Equipment (WEEE) Regulations 2013 in the UK. For this purpose, collection points for recycling centres and take-back systems (CRSO) are available from retailers or private disposal companies, which accept separate control gear and light sources free of charge. In this way, raw materials are conserved and materials are recycled.

Reference / odkazy

For more information on the multi-level guarantee and the terms and conditions of the guarantee visit [https://](https://www.inventronics-light.com/multilevel-guarantees)

- ▶ www.inventronics-light.com/multilevel-guarantees

Vyloučení odpovědnosti

Změny bez předchozího upozornění vyhrazeny. Chyby a opomenutí vyhrazeny. Vždy se ujistěte, že používáte nejnovější vydání.