## **OSRAM**

# LEDinspect WIRE-FREE SLIM 600



#### Wire-Free charging compatible

Simply place on the Wire-Free charging pad to securely hold and recharge



### Slim design

Easily place bright 600 Lumens white light where you need it most



#### **Built to last**

IK08 and IP54 rated to survive the rigors of the professional workshop



## The easiest way to recharge inspection lights

Inspection lights are a vital part of any professional's toolbox. Removing the need to find and plug into the correct charging cable, OSRAM's wire-free inspection lights recharge without hassle by simply being placed on the magnetic charging pad. This innovative design not only enhances convenience but also supports an uninterrupted workflow.

## Product family datasheet

## Technical data

	Product information	General Product Information	Electrical Data	
Product description	Application (Category and Product specific)	Global order reference	Nominal voltage	Nominal wattage
INSPECTION LAMP	LED inspection lights	LEDIL422	3.7 V	5 W

	Photometric Data			Physical Attributes & Dimensions
Product description	Light color	Nominal luminous	Color temperature	Height
	LED	flux		
INSPECTION LAMP	White	600 lm	5700 K	37.0 mm

				Lifetime Data
Product description	Width	Length	Product weight	Guarantee
INSPECTION LAMP	43.0 mm	325.0 mm	240.00 g	2 years
INSPECTION LAMP	43.0 mm	325.U mm	240.00 g	2 years

	Capabilities	Logistical data	Environmental & Regulatory Information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)	
Product description	Technology	Watt hour per battery	Candidate list substance 1	CAS No. of substance
INSPECTION LAMP	LED	9.20	Lead	7439-92-1

Safe use instruction	Declaration no. in SCIP database
The identification of the Candidate List substance is sufficient to allow safe use of the	39eac002-3892- 45bc-922c- 294d6f9430fb
	The identification of the Candidate List substance is sufficient to allow

## Product family datasheet

## Download Data

## File



User instruction

LEDinspect WIRE-FREE SLIM 600



User instruction

GPRS\_Safety symbols instructions

## **Application advice**

For more detailed application information and graphics please see product datasheet.

## Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.